

Stationary good value infrared sensor for non-contact temperature measurement of non-metallic surfaces or painted, coated or anodized metals.

## IN 2000 • IN 3000

CE

- IN 2000: Digital infrared sensor with 4-20 mA analog output and interface output for PC connection with USB
- IN 3000: Analog infrared sensor with 3 different outputs: 10 mV/°C, thermocouple type K or J
- Built-in air purge unit to keep clean the lens in dusty environments
- Easy installation and connecting
- Stainless steel housing with PG 11 thread for easy mounting
- Very small housing dimensions, suited for use in confined spaces
- Up to 70°C operating temperature without cooling

**IN 2000** and **IN 3000** are good value stationary infrared sensors for non-contact temperature measurement of non-metallic surfaces or painted, coated or anodized metals.

The small housing dimensions enable the integration of the instruments in compact production machines; the solid and robust design of the instrument guarantees reliability even in rough industrial environments. With the built-in air purge the lens can be protected from contamination with dust and moisture. This enables the instrument to be adapted to various measuring tasks. The **IN 3000** is an analog measuring device that provides 3 different outputs.

The **IN 2000** is a digital pyrometer equipped with a interface output for connection to an USB adapter. This enables the adjustment of all pyrometer parameters via PC.

#### Dimensions:

# Typical applications are measurements of:

- Plastics
- Textile
- Asphalt
- Rubber
- Paint
- Glass
- WoodVarnish
- varnis
- Ceramic
  - Paper
  - Liquids
  - Food
  - Painted metals
- Coated metals
- Anodized metals



#### Technical data

	IN 2000	IN 2000					
Tomporatur rango(s):	32 to 000 °C						
Sub range:	-52 to 900 C						
Sub lange.	minimum coon 51°C	-					
Spectral range:							
Internal signal processing:							
Power supply:	15 to 30 V DC	18 to 30 V DC					
Output:	Analog output 4 to 20 mA	10 mV//°C or					
ouput	digital output for connecting a USB adapter	thermocouple type J or K					
Load:	max. $375 \Omega$ at 15 V up to max. $1125 \Omega$ at 30 V	min. 50 k $\Omega$					
Resolution:	0.1°C on interface.						
	< 0.025% of temp. range at the analog output						
Emissivity ε:	10.0 to 100.0% (adjustable via interface)	95% (fixed)					
Transmissionsgrad T:	10.0 to 100.0% (adjustable via interface)	-					
Exposure time t <sub>90</sub> :	95 ms (adjustable to 0.5 up to 120 s) 300 ms						
Interface parameters:	Temp. display in °C or °F, emissivity ε, exposure –						
	time t <sub>90</sub> , settings of the max. / minimum value stor-						
	age, temperatur sub range, ambient temperature						
	compensation, adresse, baud rate						
Maximum / minimum value	Clear times t <sub>clear</sub> = OFF; 0.1 up to 25 s	-					
storage:	or automatically with the next measuring object						
Uncertainty:	1% of measured value + $1^{\circ}C^{-1}$ ( $\epsilon$ =1, $T_{amb.}$ =1540°C)	1.5% of temperature range or 2.5°C <sup>2)</sup>					
	1.4% of measured value + 1°C <sup>1</sup> ) (ε=1, T <sub>amb.</sub> =015 or 4070°C)						
Repatability:	< 0.3% of measured value (E=1)	1% of measured value or 1°C <sup>2)</sup>					
Noise (NETD, σ=1):	< $0.2^{\circ}C$ ( $\epsilon$ =1, t <sub>90</sub> =min, T <sub>amb.</sub> =23°C) < $0.2^{\circ}C$						
Ambient temperature:	0 to 70°C						
Storage temperature:	-20 to 70°C						
Relative humidity:	No condensing conditions						
Housing:	Stainless steel						
Weight:	150 g						
Mounting position:	Any						
Connection cable:	2 m	1 m					
Air purge unit:	For connecting hose with 2 mm inner diameter						
Protection class:	IP65 (DIN 40050)						
CE label:	According to EU directives about electromagnetic immunity						

<sup>1)</sup> The instrument must be at a constant ambient temperature for a minimum of 15 minutes and has to be connected to the power supply. <sup>2)</sup> the larger value is valid

### Optics

The optics is fixed to a distance of 50 mm, i.e. at this distance the optic achieves its smallest spot size in relation to the measuring distance. The spot size will enlarged in any other distance (shorter or longer). Please note that the measuring object must be at least as big as the spot size.



#### **Reference numbers**

	IN 2000	IN 3000			3 890 600	Power supply 24 V DC
Output:	4 to 20 mA	10 mV / °C	Type J	Type K	3 826 650	USB adapter
0 to 120°C	_	3 885 710 (0 to 1.2 V)	3 885 720	3 885 730	] 3 837 180 ] 3 835 250   3 834 250	Cooled enclosure
0 to 300°C	-	3 885 750 (0 to 3 V)	3 885 760	3 885 770		90° mirror
100 to 500°C	-	3 885 810 (1 to 5 V)	3 885 820	3 885 830		Mounting angle, fixed
-32 to 900°C	3 885 200	_	_	-	3 834 260	Mounting angle, adjusta

#### LumaSense Technologies

Americas and Australia Sales & Service 3301 Leonard Court Santa Clara, CA 95054 Tel.: +1 408 727-1600 Fax: +1 408 727-1677 info@lumasenseinc.com Europe, Middle East, Africa Sales & Service D-60326 Frankfurt, Germany Kleyerstr. 90 Tel.: +49 69 97373-0 Fax: +49 69 97373-167 India Sales & Support Center Mumbai, India **China** Sales & Support Center Shanghai, China

Tel.: +91 22 67419203 Fax: +91 22 67419201 Tel.: +86 21 5882 2277 Fax: +86 21 5887 0077

Visit lumasenseinc.com for local sales representation

© 2010 LumaSense Technologies, Rev. 12/2010. All rights reserved.